

# DATASHEET

## Variable Speed Drives



### Main Features

Reference : 5171104  
 Product code : CFW110054T2ON1Z  
 Product line : CFW11

### Basic data

Power supply : 200-240 V  
 Input minimum-maximum voltage : 170-264 V  
 Number of phases : 3  
 Input : 3  
 Output : 3

Supply voltage range	200-240 V		200-240 V	
	Normal (ND)	Heavy (HD)	Normal (ND)	Heavy (HD)
Overload regime				
Rated current	54A	45		
Overload current at 60 s	59,4A	67,5A		
Overload current at 3 s	81A	90.0		

### Maximum applicable motor

Voltage/Frequency	Power (HP / kW) [1]	
	Normal Overload (ND)	Heavy Overload (HD)
220V / 50Hz	20 / 15	15 / 11
220V / 60Hz	20 / 15	15 / 11
230V / 50Hz	20 / 15	15 / 11
230V / 60Hz	20 / 15	15 / 11

Dynamic braking [2] : Standard with braking  
 Electronic supply : Internal  
 Safety Stop : No  
 RFI internal filter [3] : Without filter  
 External filter : Not available  
 Link Inductor : Yes  
 Memory card : Included in the product  
 USB port : Standard in the product  
 Line frequency : 50/60Hz  
 Line frequency range (minimum - maximum) : 48-62 Hz  
 Phase unbalance : Less or equal to 3% of input rated line voltage  
 Transient voltage and overvoltage : Category III  
 Rated current of single-phase input :  
 - Overload (ND) :  
 - Overload (HD) :  
 Rated current of three-phase input :  
 - Overload (ND) : 54A  
 - Overload (HD) : 45 A  
 Typical input power factor : 0,94  
 Displacement factor : 0,98  
 Rated efficiency : ≥ 97%  
 Maximum connections (power up cycles - on/off) per hour : 60  
 DC power supply : Allow  
 Standard switching frequency :  
 - Overload ND : 5 kHz  
 - Overload HD : 5 kHz  
 Selectable switching frequency : 1,25; 2; 2,5; 5 and 10 kHz  
 Real-time clock : Yes, in the HMI  
 COPY Function : Yes, by HMI/MMF  
 Dissipated power:

Mounting type	Overload		Overload (*)	
	ND	HD	ND	HD
Surface	680 W	540 W	Not applicable	Not applicable
Flange	100 W	80 W	Not applicable	Not applicable

### Source available to the user

Output voltage : 24 Vcc  
 Maximum capacity : 500 mA

### Control/performance data

Power supply : Switched-mode power supply  
 Control method - induction motor : V/f, VVW, Vector and PM motor  
 Encoder interface : Only with 'Slot 2' accessory

# DATASHEET

## Variable Speed Drives



### Control/performance data

Control output frequency	: 0 to 300 Hz
Frequency resolution	: Equivalent to 1 rpm
V/F Control	
- V/F speed regulation - induction motor	: 1% of rated speed
- V/F speed variation - induction motor	: 1:20
VVW Control	
- VVW speed regulation - induction motor	: 1% of rated speed
- VVW speed variation - induction motor	: 1:30
Sensorless vector control	
- SLV speed regulation - induction motor	: 0,5% of rated speed
- SLV speed variation - induction motor	: 1:100
Vector control with encoder	
- ENC speed regulation - induction motor	: 0,05% of rated speed
- ENC speed variation - induction motor	: Up to 0 rpm

### Analog inputs

Quantity (standard) AI	: 2
AI levels	: 0-10V, 0/4-20mA and -10-+10V
Impedance	
- Impedance for AI voltage input	: 400 kΩ
- Impedance for AI current input	: 500 Ω
AI function	: Programmable
Maximum allowed voltage AI	: ±30 Vcc

### Digital inputs

Digital inputs - Quantity (standard)	: 6
Activation	: Active low and high
DI maximum low level	: 3 V
DI minimum high level	: 18 V
Input current	: 11 mA
Maximum input current DI	: 13,5 mA
Function	: Programmable
Maximum allowed voltage	: 30 Vcc

### Analog outputs

Analogic outputs - Quantity (standard)	: 2
Levels	: 0 to 10V, 0 to 20mA and 4 to 20mA
RL for voltage output	: 10 kΩ
RL for AO current output	: 500 Ω
Function	: Programmable

### Digital outputs

Digital outputs - Quantity (standard)	: 3 NO/NC relays
Maximum voltage	: 240 Vca
Maximum current DO - transistor	: 1 A
Function	: Programmable

### Communication

- Modbus-RTU (with accessory: RS485-01; RS485-05; CAN/RS485-01; RS232-01 or RS232-05)
- Modbus/TCP (with accessory: MODBUSTCP-05)
- Profibus DP (with accessory: PROFDP-05)
- Profibus DPV1 (with accessory: PROFIBUS DP-01)
- Profinet (with accessory: PROFINETIO-05)
- CANopen (with accessory: CAN/RS485-01 or CAN-01)
- DeviceNet (with accessory: DEVICENET-05; CAN/RS485-01 or CAN-01)
- EtherNet/IP (with accessory: ETHERNET/IP-05 or ETHERNETIP-2P-05)
- EtherCAT (with accessory: ETHERCAT-01)
- BACnet (with accessory: RS485-01 or CAN/RS485-01)

### Protections available

- Output overcurrent/short circuit
- Power supply phase loss
- Under/Overvoltage in power
- Overtemperature
- Motor overload
- IGBT's modules overload
- Fault/External alarm
- Breaking resistor overload
- CPU or memory failure
- Output phase-ground short circuit

### Operation interface (HMI)

Availiability	: Included in the product
HMI installation	: Local
Number of HMI buttons	: 9
Display	: Graphic LCD
Indication accuracy	: 5% of rated current
Speed resolution	: 1 rpm

# DATASHEET

## Variable Speed Drives



### Operation interface (HMI)

Standard HMI degree of protection	: IP56
HMI battery type	: CR2032
HMI battery life expectancy	: 10 years
Remote HMI type	: Detachable of the inverter
Remote HMI frame	: Accessory
Remote HMI degree of protection	: IP56

### Ambient conditions

Enclosure	: NEMA1
Pollution degree (EN50178 and UL508C)	: 2
Temperature	
- Minimum	: -10 °C / 14 °F
- Nominal [4]	: 50 °C / 122 °F
Current reduction factor [5]	: 2 % per °C of 50 (122) o 60 °C (140 °F)
Relative humidity (non-condensing)	
- Minimum	: 5%
- Maximum	: 90%
Altitude	
- Rated conditions	: 1000 m (3281 ft)
- Maximum altitude allowed for operation	: 4000 m (13123 ft)
Current Reduction factor[6]	
- Current derating factor (for altitudes above rated)	: 1% for each 100 m above (0,3% for each 100 ft above)
- Voltage derating factor (for altitudes above 2000 m / 6562 ft)	: 1,1% for each 100 m above (0,33% for each 100 ft above)

### Sustainability policies

RoHS	: Yes
Conformal Coating	: 3C2 (IEC 60721-3-3:2002)

### Dimensions

Size	: C
Height	: 479 mm / 18.8 in
Width	: 220 mm / 8.66 in
Depth	: 293 mm / 11.5 in
Weight	: 16.9 kg / 37.2 lb

### Mechanical installation

Mounting position	: Surface or flange
Fixing screw	: M6
Tightening torque	: 8,5 N.m / 6.27 lb.ft
Allows side-by-side assembly	: Yes, without top cap
Minimum spacing around the inverter	
- Top	: 110 mm / 4.33 in
- Bottom	: 130 mm / 5.12 in
- Front	: 10 mm / 0.39 in
- Minimum spacing around inverter	: 30 mm / 1.18 in

### Electrical connections

Cable gauges and tightening torque:

	Recommended cable gauge to 75 °C (167 °F)	Recommended tightening torque
Power	16,0 mm <sup>2</sup> (6 AWG)	2,7 N.m / 1,99 lb.ft
Braking	10,0 mm <sup>2</sup> (8 AWG)	2,7 N.m / 1,99 lb.ft
Grounding	16,0 mm <sup>2</sup> (6 AWG)	3,5 N.m / 2.58 lb.ft
Control	0,5 to 1,5 mm <sup>2</sup> (20 to 14 AWG)	0,5 N.m / 0.37 lb.ft

### Additional specifications

Maximum breaking current	: 48,8 A
Minimum resistance for the brake resistor	: 8.2 Ω
Recommended aR fuse	: FNH00-80K-A
Recommended aR fuse	: Not applicable
Recommended circuit breaker	: ACW100H-FMU63-3
Recommended circuit breaker	: Not applicable

### Standards

Safety	<ul style="list-style-type: none"> <li>- UL 508C - Power conversion equipment.</li> <li>- UL 840 - Insulation coordination including clearances and creepage distances for electrical equipment.</li> <li>- EN 61800-5-1 - Safety requirements electrical, thermal and energy.</li> <li>- EN 50178 - Electronic equipment for use in power instalations</li> <li>- EN 60204-1 - Safety of machinery. Electrical equipment of machines. Part 1: General requirements. Note: To have a machine in accordance with this standard, the machine manufacturer is responsible for installing an emergency stop device and supply disconnecting device.</li> <li>- EN 60146 (IEC 146) - Semiconductor converters.</li> <li>- EN 61800-2 - Adjustable speed electrical power drive systems - Part 2: General requirements - Rating especifications for low voltage adjustable frequency AC power drive systems.</li> </ul>
--------	---

# DATASHEET

## Variable Speed Drives



<p>Electromagnetic compatibility</p>	<p>EN 61800-3 - Adjustable speed electrical power drive systems - Part 3: EMC product standard including specific test methods.                      - EN 55011 - Limits and methods of measurement of radio disturbance characteristics of industrial, scientific and medical (ISM) radio-frequency equipment.                      - CISPR 11 - Industrial, scientific and medical (ISM) radio-frequency equipment - Elettromagnetic disturbance characteristics - Limits and methods of measurement.                      - EN 61000-4-2 - Elettromagnetic compatibility (EMC) - Part 4: Testing and measurement techniques - Section 2: Eletrostatic discharge immunity test.                      - EN 61000-4-3 - Elettromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 3: Radiated, radio-frequency, electromagnetic field immunity test.                      - EN 61000-4-4 - Elettromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 4: Electrical fast transient/burst immunity test.                      - EN 61000-4-5 - Elettromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 5: Surge immunity test.                      - EN 61000-4-6 - Elettromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 6: Immunity to conducted disturbances, induced by radio-frequency fields.</p>
<p>Mechanical construction</p>	<p>- EN 60529 - Degrees of protection provided by enclosures (IP code).                      - UL 50 - Enclosures for electrical equipment.                      - EN 60529 e UL 50</p>

### Certifications

#### Notes

- 1) Orientative motor power, valid for WEG Motors standard of IV poles. The correct sizing must be done according to the nominal current of the motor used, which must be less than or equal to the rated output current of the inverter.
- 2) Braking resistor is not included.
- 3) With category for emission level conducted.
- 4) Without derating and with minimum spaces.
- 5) For temperatures above the nominal and maximum temperature (with derating of current and minimum spaces).
- 6) For altitude over of specified.
- 7) All images are merely illustrative.